

Hi3516C V300 Professional HD IP Camera SoC

# **Brief Data Sheet**

Issue 03

Date 2016-11-10

## Copyright © HiSilicon Technologies Co., Ltd. 2016. All rights reserved.

No part of this document may be reproduced or transmitted in any form or by any means without prior written consent of HiSilicon Technologies Co., Ltd.

#### **Trademarks and Permissions**

HISILICON, and other HiSilicon icons are trademarks of HiSilicon Technologies Co., Ltd.

All other trademarks and trade names mentioned in this document are the property of their respective holders.

#### **Notice**

The purchased products, services and features are stipulated by the contract made between HiSilicon and the customer. All or part of the products, services and features described in this document may not be within the purchase scope or the usage scope. Unless otherwise specified in the contract, all statements, information, and recommendations in this document are provided "AS IS" without warranties, guarantees or representations of any kind, either express or implied.

The information in this document is subject to change without notice. Every effort has been made in the preparation of this document to ensure accuracy of the contents, but all statements, information, and recommendations in this document do not constitute a warranty of any kind, express or implied.

# HiSilicon Technologies Co., Ltd.

Address: Huawei Industrial Base

> Bantian, Longgang Shenzhen 518129

People's Republic of China

Website: http://www.hisilicon.com

Email: support@hisilicon.com



## **Key Specifications**

#### **Processor Core**

ARM926@800 MHz with 32 KB I-cache and 32 KB D-cache

#### Video Encoding

- H.264 BP/MP/HP
- H.265 Main Profile
- MJPEG/JPEG baseline

### **Video Encoding Performance**

- Maximum 2-megapixel resolution for H.264/H.265 encoding
- Real-time multi-stream H.264/H.265 encoding capabilities
  - 1920x1080@45 fps
  - 1920x1080@30 fps+720x480@30 fps+360x240@30 fps
- JPEG snapshot at 2 megapixels@5 fps
- CBR, VBR, FIXQP, AVBR, and QPMAP modes
- Maximum 30 Mbit/s output bit rate
- Encoding of eight ROIs

### **Intelligent Video Analysis**

Integrated IVE, supporting various intelligent analysis applications such as motion detection, perimeter defense, and video diagnosis

### Video and Graphics Processing

- 3DNR, image enhancement, and DCI
- Anti-flicker for output videos and graphics
- 1/15x to 16x video and graphic scaling
- Overlaying of video and graphics
- Picture rotation by 90°, 180° or 270°
- Picture mirroring and flipping
- OSD overlaying of eight regions before encoding

## ISP

- 3A (AE, AF, and AWB) function. The third-party 3A algorithms are supported.
- FPN removal and DPC
- LSC, LDC, and purple edge correction
- Direction-adaptive demosaic
- Gamma correction, DCI, and color management and enhancement
- Adaptive region de-fog
- Multi-level NR (BayerNR and 3DNR) and sharpening enhancement
- Local tone mapping
- Sensor built-in WDR and 2F WDR (line-base/frame-base/DCG)
- DIS
- ISP tuning tools for the PC

### **Audio Encoding/Decoding**

- Voice encoding/decoding complying with multiple protocols by using software
- Compliance with the G.711, G.726, and ADPCM protocols

• Audio 3A functions (AEC, ANR, and AGC)

#### **Security Engine**

- Various encryption and decryption algorithms implemented by using hardware, including AES, DES, 3DES, and RSA
- HASH (SHA1/SHA256/HMAC\_SHA/HMAC\_SHA256) algorithms implemented by using hardware
- Integrated 512-bit OTP storage space and random number generator

#### Video Interfaces

- VI interfaces
  - 8-/10-/12-/14-bit RGB Bayer DC timing VI
  - BT.601, BT.656, and BT.1120 VI interfaces
  - MIPI, LVDS/sub-LVDS, and HiSPi
  - Compatibility with mainstream HD CMOS sensors provided by Sony, ON, OmniVision, and Panasonic
  - Compatibility with the electrical specifications of parallel and differential interfaces of various sensors
  - Programmable sensor clock output
  - Maximum input resolution of 2048 x 2048, up to 198 megapixels/s
- VO interfaces
  - One PAL/NTSC output for automatic load detection
  - One BT.656 VO interface
  - 6-bit RGB565 serial LCD output

#### **Audio Interfaces**

- Integrated audio CODEC supporting 16-bit audio inputs and outputs
- Mono-channel differential MIC inputs for reducing the background noises
- Single-ended dual-channel input
- I<sup>2</sup>S interface for connecting to the external audio CODEC

### **Peripheral Interfaces**

- POF
- One integrated high-precision RTC
- Integrated 3-channel LSADC
- Three UART interfaces (including one 4-wire interface)
- IR, I<sup>2</sup>C, SPI, and GPIO interfaces
- Four PWM interfaces
- Two SDIO 2.0 interfaces, supporting the 3.3 V level and 1.8 V level
- One USB 2.0 host/device port
- RMII in 10/100 Mbit/s full-duplex or half-duplex mode, TSO network acceleration, and PHY clock output

### **External Memory Interfaces**

- SDRAM interface
  - 16-bit DDR3/DDR3L interface with the maximum capacity of 4 Gbits
- SPI NOR flash interface
  - 1-/2-/4-wire mode
  - Maximum capacity of 32 MB
- SPI NAND flash interface with maximum 4 Gbits capacity



- SD card interface supporting the maximum capacity of 2 TB
- eMMC 4.5 interface with 4-bit data width

#### **Boot**

- Booting from the SPI NOR flash, SPI NAND flash, or eMMC
- Secure boot


#### **SDK**

- Linux-3.18-based SDK
- High-performance H.264 PC decoding library
- High-performance H.265 PC/Android/iOS decoding library

### **Physical Specifications**

- Power consumption
  - 1080p30, typical power consumption of 550 mW
  - Deep standby wakeup
- Operating voltages
  - 0.9 V core voltage
  - 3.3 V±10% I/O voltage
  - 1.35 V or 1.5 V DDR3/3L SDRAM interface voltage
- Package
  - Body size of 12 mm x 12 mm (0.47 in. x 0.47 in.), 0.65 mm (0.03 in.) ball pitch, TFBGA RoHS package with 273 pins


## **Functional Block Diagram**



Hi3516C V300 is a new-generation SoC designed for the industry-dedicated HD IP camera. It has an integrated new-generation ISP and the latest H.265 video compression encoder in the industry. It uses the advanced low-power technology and architecture design. All of these features enable Hi3516C V300 to lead the industry in the low bit rate, high profile, and low power consumption. Hi3516C V300 integrates the POR, RTC, audio CODEC, and standby wakeup circuit, which significantly reduces customers' EBOM cost. In addition, the interface design similar to that of other HiSilicon DVR and NVR chips facilitate development and mass production of customer's products.



## Hi3516C V300 HD IP Camera Solution





# Acronyms and Abbreviations

3DES Triple Data Encryption Standard

ADPCM adaptive differential pulse code modulation

AE automatic exposure

AEC acoustic echo cancellation

AES Advanced Encryption Standard

AF automatic focus

ALC automatic level control

ANR audio noise reduction

AVBR adaptive variable bit rate

AWB automatic white balance

CBR constant bit rate

CMOS complementary metal-oxide-semiconductor

CODEC coder/decoder

DC direct current

DCI dynamic contrast improvement

DDR double data rate

DES Data Encryption Standard

DIS digital image stabilization

DNR digital noise reduction

DPC defect pixel correction

DVR digital video recorder

EBOM engineering bill of materials

eMMC embedded multimedia card

FPN fixed pattern noise

GPIO general-purpose input/output

HD high definition

HiSPi high-speed serial pixel interface

I<sup>2</sup>C inter-integrated circuit

I<sup>2</sup>S inter-IC sound

IR infrared



ISP image signal processor

IVE intelligent video engine

LCD liquid crystal display

LDC lens distortion correction

LSC lens shading correction

LVDS low voltage differential signal

MIC microphone

MIPI mobile industry processor interface

NR noise reduction

NTSC National Television System Committee

NVR network video recorder

OSD on-screen display

OTP one-time programmable

PAL phase alternating line

POR power-on reset

PWM pulse-width modulation

RMII reduced media independent interface

RoHS Restriction of Hazardous Substances

ROI region of interest

RSA Rivest-Shamir-Adleman

RTC real-time clock

SAR ADC successive approximation register analog-to-digital converter

SDHC Secure Digital High Capacity

SDIO secure digital input/output

SDK software development kit

SDRAM synchronous dynamic random access memory

SoC system-on-chip

SPI serial peripheral interface

TFBGA thin & fine ball grid array
TSO TCP segmentation offload

TILDE

UART universal asynchronous receiver transmitter

VBR variable bit rate



VGA video graphics array

VI video input

VO video output

WDR wide dynamic range